Step 1:



Download Di866 USB firmware from Nissin official website. File name: Setup.exe

Installing		
Please wait while DiB66 [DM Startup 1.0 is being installed.	
Downloading Di856_DM.	exe	
785kB (25%) of 3166kB at 196.3kB/s (12 seconds	remaining)
785kB (25%) of 3166kB at 196.3kB/s (12 seconds	remaining)
785kB (25%) of 3166kB at 196.3kB/s (12 seconds	remaining)
785kB (25%) of 3166kB at 196.3kB/s (12 seconds	remaining)
785kB (25%) of 3166kB at 196.3kB/s (12 seconds	remaining)

Double-click to install.



Press "OK" button to continue.

		Completing the I 1.0 Setup Wizard	Di866 DM Startup d	
	ACDZip Self-E	tracting Archive	all an other	
	Exhact To	extract all the files in Di866_0	DM.exe press the Extract butto	·n.
	Destination Folder:			1
	C.VProgram Files\	1865_214		Browse
10	Overwrite files			
15	Extract	Cancel		About
	ALC: NOT THE OWNER			

Press "Extract" button to continue the installation.



Press "Finish" button to run the program when the "Download Manger Main Program" installed successfully .



Go to "Software" page.

About Software	Download			
	Model			
	Select M	lodel :	Nikon	
	Current Firn	A You	ur Current versior	n is lasted updated
	Updated Firm			确定
Click	to get updated Fir			_

In "Model" section, please select the model of Di866. If there is a red box notice prompted with "Your Current version is lasted updated". This means the Di866 firmware has currently updated from Nissin official website and click OK.



Following the Step1-3, connect USB cable and Di866, and continue the download.



Make sure the cable has been connected successfully. A white screen indicates that Di866 is in the download mode.

(a) If this is the first time to update the Di866, please go to he Step 10.

(b) If the Di866 has been updated in the past, press Download button directly and go to Step 11.

Step 10:





When windows found the new hardware, click Locate and install driver software. Follow the steps to install.

Browse the location and click Next.

G 1	Eound New Hardware - AT90USB162 DFU
B	Prowse for driver software on your computer
S	earch for driver software in this location:
	C:\Program Files\Di866_DM
	Include subfolders
	Next Cancel

Click Install.



Please wait while installing driver software.

	X
🕞 📱 Found New Hardware - AT90USB162 DFU	
Installing driver software	

Press Close when the install completed.

Found New Hardware - AT90USE162	
The software for this device has b	een successfully installed
Windows has finished installing the driver se	oftware for this device:
AT90USB162	
•	
	Close

Step 11:

About Software Download	1	
Procedure :	and the second se	PROPERSO
Sten 4. Download is finis	Please disconnect	
Download Complete 确定	B66 again. tch. are] page ersion.	
Press [Download] button	e, then to start the	Ţ
download process Download Success		Repeat Step
Connect Status		
Internet Commented		Download

When the download completed, click OK.

Step 12:

Nissin Di866 Download Manager	
Nissin Di866 Download Manager	
About Software Download	
Procedure :	
Step 4. Download is finished. Please disconnect	Dilet
the USB cable, then unload the Battery	Pilot
Cartidge to leave the Download mode.	Set On/Off
Then Switch ON the Di866 again.	A
** You may go to [Software] page	
to check the firmware version.	
Download Success	Repeat Step
Connect Status	
Network Connected	Dowpload
	Southour

When red blank shows "Download success," disconnect the USB cable. The white screen should still remain in the flash unit. Unloading the battery cartridge. Leave the download Manager when completed.